




Owner's Manual

Bluetooth Helmet Headset

SALUT

1. Headset Buttons



M: 1. Play/Pause [cell phone music]

2. Redial last phone number

3. Cell phone voice dials

A: to select 1-on-1 intercom with A1, A2 or A3 headset

V+: 1. Next track [cell phone music]

2. Volume up

3. To adjust sound volume, set activation mode for 1-on-1 intercom


V-: 1. Previous track [cell phone music]

2. Volume down

3. To adjust sound volume, set activation mode for 1-on-1 intercom


Refer to Section 8: Quick Operation Reference Table for detailed SALUT headset button functions.

2. Recharge




1. Use Mini USB cable to recharge. During recharging, LED stays red. When charged, LED stays blue. Headset battery is initially partially charged. Please fully recharge the headset before the first use.
2. Low battery warning: When battery is low, 3 <beeps> can be heard (i.e., <beep><beep><beep>) is heard to remind the user to recharge.

3. Power ON/OFF



1. Power ON: Press both A and V- buttons simultaneously until LED stays blue and release both button.
2. Power OFF: Press A and V- buttons simultaneously until the LED stays red. A voice notification can be heard to inform you the remaining battery capacity.

4. Pair with Cell Phone and Use



4.1 Pair with Cell Phone

1. Turn on SALUT, press M until the LED flashes red/blue alternatingly.
2. Ice name: SALUT, and connect. Activate cell phone Bluetooth. Search for device SALUT and connect.
3. When asked for password, input <0000> (4 zeros). After connection, a voice notification <Bluetooth device pairing complete> is heard, and the LED flashes blue slowly to indicate successful pairing.

4.2 Use Cell Phone

1. Press M to answer incoming call.
2. When auto-answer is set, the incoming call will be automatically answered after ringing for 10 seconds.
3. To end a call, press M once, or wait for the other party to end the call.
4. To reject a call, press M for 3 seconds. (Note: when auto-answer is off, the call is automatically rejected after ringing for 16 seconds.)
5. Voice dial: Press M once and speak into the phone (cell phone must provide voice dial function.)

6. Redial last number: Press M twice rapidly, the cell phone will redial the last call-out number.
7. When paired with two cell phones to redial the last number on the second cell phone, press M 3 times rapidly.
8. To reconnect cell phone, press M to reconnect. (When paired with two cell phones, both cell phones are reconnected.)
9. When connected to two cell phones if the second cell phone has an incoming call during the first cell phone talk, press A to answer the incoming call on the second cell phone and hold the first cell phone. When the call on the second phone ends, the headset will resume the first cell phone.
10. Set Auto-Answer: Hold both M and V+ for 8 seconds. A voice notification <cell phone answer mode> <automatic answer> can be heard to indicate successful setting.
11. Disable Auto-Answer: Hold both M and V- for 8 seconds. A voice notification <cell phone answer mode> <manual answer> can be heard to indicate auto-answer is disabled.
12. Cell phone music (AVRCP)
Play/Pause: press M for 2 seconds.
Next track: press V+ twice.
Previous track: press V- twice.

4.3 Cell phone Volume

Volume UP: press V+.

Volume DOWN: press V-.

When adjusting volume, a sound <dun-dun> can be heard. When reach the maximum or minimum volume, a <beep> tone can be heard. To adjust cell phone and headset volume, the cell phone function must be activated and the cell phone must be in talk or in music play mode.

5. Headset and GPS Pairing and Usage

5.1 Pairing with a GPS

1. Starting with the SALUT headset in ON state, press the [M] button until the LED flashes red/blue.
2. Activate the Bluetooth function on GPS to search for the SALUT, and connect.
3. If the device asks for a password, input password <0000> (four zeros) to complete the connection. The LED flashes blue slowly to indicate successful pairing.

Note: SALUT supports simultaneous connection to both GPS and cell phone.

5.2 GPS Usage

If you have paired your SALUT with a GPS, vocal GPS directions can be heard through the headset. If you are on an intercom with another SALUT headset when the GPS audio instruction comes in, the intercom connection will be automatically paused. The intercom connection resumes after the GPS instruction is over. When your SALUT headset is connected to a cell phone and a GPS audio instruction comes in, you can hear both the GPS instructions and the cell phone.

5.3 Adjusting GPS volume

Press the knob [V+] and [V-] buttons on SALUT headset upward or downward to adjust the volume of the GPS when connecting to the headset. During adjustment, an audible tone will be heard. When the volume reaches the maximum or the minimum setting, an audible tone/beep will be heard. The GPS must be activated to adjust the volume of the GPS during GPS broadcasting instruction.

6. 1-On-1 Intercom Headset Pairing and Usage


Two SALUT headsets must be paired for 1-on-1 intercom.

Each SALUT can connect to 3 (at most) other SALUT headsets for 1-on-1 intercom. The three SALUT headsets will be defined, according to the reverse time order they were paired, as: (i.e., the most recently paired has the highest priority)

first priority: "Comm A1", second priority: "Comm A2", and third priority: "Comm A3" .

6.1 1-on-1 Intercom Pairing

1. SALUT headset#1 is turned on, pressed A until the LED flashes blue rapidly.
2. SALUT headset#2 is turned on, press M until the LED flashes red/blue alternatingly and rapidly.



After the above two steps, the two headsets will automatically pair with each other until the LED on both headsets flashes blue. At this point, two headsets can intercom with each other directly and both headsets can hear a voice notification <headset A pairing completed>.

3. After pairing, SALUT #1 places SALUT#2 as its first priority (A1). If SALUT#1 paired with other headsets earlier, the previously A1 will be pushed back as A2, and previously A2 becomes A3 and the previously A3 will no longer be recorded.
4. Also, after pairing, SALUT#2 places SALUT#1 as its first priority (A1). If SALUT #2 paired with other headsets earlier, the previously A1 will be

pushed back as A2, and previously A2 becomes A3 and the previously A3 will no longer be recorded.

6.2 1-on-1 Intercom Usage

Paired SALUT headsets for 1-on-1 intercom can start intercom transmission in two modes:

Manual mode.

The default mode when SALUT headsets are shipped is manual mode. When SALUT is powered on, the user will hear "VOX sensitivity Manual Mode"

6.2.1 Manual Mode for starting 1-on-1 Intercom:

The SALUT headsets already paired for 1-on-1 intercom can use [A] to select one of the three headsets recorded in the list, as follows:

Press [A] once to start 1-on-1 intercom with A1; press [A] twice to start 1-on-1 intercom with A2; and press [A] three times to start 1-on-1 intercom with A3.

6.2.2 Manually Ending 1-on-1 Intercom

During 1-on-1 intercom, any of the tow headsets can press [A] once to end the intercom.

7. Quick Operation Reference for SALUT Headset

FUNCTION	BUTTON
INSTRUCTION	
Power ON	In OFF state, Press [A] and [V-] until LED turns blue
Power OFF	In ON state, Press [A] and [V-] until LED turns red
Cell phone/GPS/headset Pairing	In ON state, Press [M] until LED flashes red/blue

1-on-1 intercom pairing	In ON state, press [A] until LED flashes blue rapidly
Group intercom pairing	In ON state, press [V-] until LED flashes red rapidly
Volume Up	Press [V+] once (only when sound can be heard)
Volume Down	Press [V-] once (only when sound can be heard)
1-on-1 intercom activation mode - Level Up	Press [V+] twice rapidly, adjustable only when NOT in music or FM mode
1-on-1 intercom activation mode - Level Down	Press [V-] twice rapidly, adjustable only when NOT in music or FM mode
Set Automatic Answer	Press [M] and [V+] for 8 seconds until the notification "Answering Mode Automatic" is heard (only when no voices can be heard)
Setting Voice Answering	Press [M] and [V-] for 8 seconds until the notification "Answering Mode Voice " is heard (only when no voices can be heard)
CELL PHONE OPERATION	
Answering an incoming call	Press [M] to answer
Ending a call	Press [M] to end
Rejecting a call	Press [M] for about 3 seconds (when the automatic answering mode is not activated, the call will be automatically rejected after ringing for 16 seconds.)
Voice dialing	Press [M], and speak into microphone (cell phone must support voice dialing)
Redialing last call-out number	Press [M] twice rapidly
Redialing the last call-out number on the second cell phone	Press [M] three times rapidly
INTERCOM WITH A HEADSET (NOT during a cell phone call)	
Starting 1-on-1 Intercom	Press button [A] once, twice or three times rapidly to select partner and hear voice notification (Comm A1/A2/A3 selected)

	can be heard. A double tone sound will indicate a successful intercom connection.
Ending 1-on-1 Intercom	Press [A] once.
MUSIC (NOT during a cell phone call or intercom)	
Play/Pause	Press button [M] for 2 seconds and release
Previous	Press [V-] twice rapidly
Next	Press [V+] twice rapidly

8. SALUT Voice Notifications Quick Reference

State	Voice Prompt Beginning	Voice Prompt Ending
Battery Charge	"Battery Charge"	"Full" "Above 80%" "Above 50%" "Low approaching 25%" "Critical 10%" "Warning, Low battery"
Pairing (for intercom Headset)		"Bluetooth Device Paired" "Comm A Paired"
Intercom already in use		"Party occupied" "Missed A1 page" "Missed A2 page" "Missed A3 page" "intercom canceled" "Connection lost" "Auto-reconnection " "A1 connection failed" "A2 connection failed" "A3 connection failed"

Answering Mode	" Answering Mode "	"Automatic" "Voice"
Cell phone dialing		"Last Number Redial"
Cell phone must support AVRCP		"Play" "Pause" "next track" "previous track"
Version	"Version"	